

Changing Wifi Name and Password

You'll need to log into the web-based console for your residential gateway in order to change make configuration changes. To log in:

1. Connect to your residential gateway, either with an Ethernet cable or by Wi-Fi (you **do not** need to have Internet access to do this).
2. In a browser window go to <http://192.168.1.1>
3. Your username and password will be on a sticker on the unit and is unique to your residential gateway; enter them.
4. Click Login.

Change the 5GHz wireless network name and password on the Calix 844

Step 1 Log into the router

Step 2 Click on **Wireless**

Step 3 Click on **5G Network**

Step 4 Click on **SSID Setup**

Step 5 Enter the new wireless name in the **Rename SSID** field

Step 6 Click **Apply** to save your changes



Status Quick Start **Wireless** Utilities Advanced

Wireless

2.4G Network
5G Network
Radio Setup
SSID Setup
Security
MAC Authentication
WPS

Service Set Identifier (SSID)

Service Set Identifier (SSID) is used to identify this gateway device for connection to other wireless devices. The SSID may be broadcast to publish its value to aid in connecting this device to other wireless devices or it may be hidden to prevent unauthorized access. The factory-defined SSID values may be redefined to a user-specified name.

SSID (Network Name): CXNK002B5EF6

Broadcast SSID: Enabled Disabled

Rename SSID: CXNK002B5EF6

Apply

Step 7 Click on **Security**

Step 8 Click the radio button next to **Use Custom Security Key** and enter the new password

Step 9 Click **Apply** to save your changes



Status Quick Start **Wireless** Utilities Advanced

Wireless

2.4G Network
5G Network
Radio Setup
SSID Setup
Security
MAC Authentication
WPS

Security

Secure your wireless traffic as it transmits through the air.

SSID (Network Name): CXNK002B5EF6

Security type: WPA - WPA2-Personal

Encryption type: AES

Security Key / Passphrase:

Use Default Security Key: 9609c270cf42c937

Use Custom Security Key: 1234567890

Apply

Change the 2.4GHz wireless network name and password on the Calix 844

Step 1 Log into the router

Step 2 Click on **Wireless**

Step 3 Click on **2.4G Network**

Step 4 Click on **SSID Setup**

Step 5 Enter the new wireless name in the **Rename SSID** field

Step 6 Click **Apply** to save your changes



Status Quick Start **Wireless** Utilities Advanced

Wireless

- 2.4G Network
- Radio Setup
- SSID Setup**
- Security
- MAC Authentication
- WMM
- 5G Network
- WPS

Service Set Identifier (SSID)

Service Set Identifier (SSID) is used to identify this gateway device for connection to other wireless devices. The SSID may be broadcast to publish its value to aid in connecting this device to other wireless devices or it may be hidden to prevent unauthorized access. The factory-defined SSID values may be redefined to a user-specified name.

SSID (Network Name): CXNK002B5EF6

SSID State: Enabled Disabled

Broadcast SSID: Enabled Disabled

Rename SSID: CXNK002B5EF6

Apply

Step 7 Click on **Security**

Step 8 Click the radio button next to **Use Custom Security Key** and enter the new password

Step 9 Click **Apply** to save your changes



Status Quick Start **Wireless** Utilities Advanced

Wireless

- 2.4G Network
- Radio Setup
- SSID Setup
- Security**
- MAC Authentication
- WMM
- 5G Network
- WPS

Security

Secure your wireless traffic as it transmits through the air.

SSID (Network Name): CXNK002B5EF6

Security type: WPA - WPA2-Personal

Encryption type: AES

Security Key / Passphrase:

Use Default Security Key: 9609c270df42d937

Use Custom Security Key: 1234567890

Apply